PD050307



PD048953



PILOT Mi.BOXER Digital 2.4G do SPIR3

PILOT Mi.BOXER Digital 2.4G do SPIR3

- **Kontroluj wiele urządzeń jednocześnie, obsługuj komunikację z wieloma urządzeniami**
- **Zmiana trybu dynamicznego, koloru, jasności i funkcji dynamicznego oświetlenia**
- **Edycja szerokości i koloru w trybie dynamicznym**
- **Ustawianie czasu i koloru efektu ON/OFF**
- **Współpraca z wieloma kontrolerami – zasięg sterowania do 30 m**
- **Uchwyt magnetyczny ułatwiający montaż**
- **Do zastosowań w oświetleniu komercyjnym i domowym oraz oświetleniu dekoracyjnym**

- Control multi devices at the same time, support communication with multi devices
- Changing dynamic mode,color, brightness and dynamic lighting feature
- Editing width and color for dynamic mode
- Setting time and color for ON/OFF
- Working with multi controllers (control distance 30m)
- Magnetic holder with simple installation
- Wide application for commercial or home lighting, create ambience lightingSuitable for commercial, residential and decorative lighting

Kod produktu / Product code	PD050307	PD048953
Kod EAN / EAN code	5908293950307	5908293948953
Napięcie wejściowe / Input voltage	3 V (2×AAA)	
Pobór energii / Power Consumption	15μA	
Moc nadawania / Transmitting Power	6dBm	
Temperatura pracy / Working temperature	-10°C ~ 40°C	
Sygnał wejściowy / Input signal	RF 2.4 GHz	
Metoda modulacji / Modulation Method	GFSK	
Max zasięg pilota / Max controlling distance	30 m	
Normy EMC / EMC standard	ETSI EN 301 489-1 V2.2.3 ETSI EN 301 489-3 V2.3.2	
Normy bezpieczeństwa / Safety standard	EN 61347-2-11:2001+A1:2019 EN 61347-1:2015+A1:2021 EN 62493:2015 +A1:2022	
Sprzęt radiowy / Radio Equipment	ETSI EN 300 440 v 2.2.1 (2018-07)	
Certyfikaty / Certification	CE, EMC, RED	

Kompatybilny z / Compatible with:

PD048939 / STEROWNIK Mi.BOXER 3in1 (SC+RGB+RGBW) Digital 5-24V / 10A / 2048px - 1024px / 2.4 GHz



